

Analogue Wall Sounder Beacon

CHQ-WSB



Features

- ▶ Loop Powered
- ▶ Single Loop Address - addressed via the TCH-B100 Hand Held Programmer
- ▶ Variable Sound Output
90 ~ 102 dB(A) (± 2 dB(A)) output at 1 metre
- ▶ High Intensity LED technology
- ▶ Variable flash frequency*
- ▶ Fits Hochiki Standard or Isolator Base
- ▶ Weatherproof Kit available
- ▶ 51 User-Selectable Tones (all tones EN54-3 compatible)

Description

Model CHQ-WSB is an addressable loop powered Wall Sounder Beacon innovatively designed to provide a range of tones and volumes with a maximum output of up to 102dB(A) (± 2 dB(A)) with low current consumption. The unit features an integral beacon within the horn utilising high intensity LED technology and is designed to fit to the Standard Base (YBO-R/3(RED)) or the Isolator Base (YBO-R/SCI(RED)). The sounder is IP rated to IP21 for internal use but it can be made weatherproof by utilising the WS2-WPK Weatherproof Kit, which consists of a specialised back box and gasket set.

Also incorporates an auto shutdown mode* which allows the user to set a fixed time within which the sounder will operate, before automatically silencing itself, ideal for minimising noise pollution.

Specification

Ordering Codes	CHQ-WSB WS2-WPK (Weatherproof Kit)
Operating Voltage	17 ~ 41 VDC
Quiescent Current (typ)	150 μ A (with YBO-R/3(RED)) 200 μ A (with YBO-R/SCI(RED))
Sounding Current (typ)	2 mA (90 dB(A) (± 2 dB(A)) @ 1 m) ~ 8 mA (102 dB(A) (± 2 dB(A)) @ 1 m)
Additional Current when Beacon active	+ 5 mA
Sound Output (at 1 metre)	90 ~ 102 dB(A) (± 2 dB(A)) @ 24 VDC or above
Number of Tones	51
Tone Frequency Range	300 Hz ~ 2850 Hz
Operating Temperature Range	-10 $^{\circ}$ C to +50 $^{\circ}$ C
Storage Temperature Range	-30 $^{\circ}$ C to +70 $^{\circ}$ C
Maximum Humidity	95% RH - Non Condensing (at 40 $^{\circ}$ C)
Colour/Case Material	Red / PC ABS
Ingress Protection Rating	IP21 (IP65 with WS2-WPK)
Weight (g)/Dimensions (mm)	164 / H112 x W112 x D67
Base Fixing Centres (mm)	48 ~ 74

*Dependent on control panel compatibility.

Note: Although the TCH-B100 Hand Held Programmer will allow addresses between 128 and 254 to be programmed into the CHQ-WSB, addresses 1 to 127 ONLY should be used.